



**DATOS TECNICOS**

**RELACION ENTRE POLEA, NRO DE CANALES Y TIPO DE BUJE CONICO**

5V

DIAMETRO Correa 5V	DIAMETRO EXTERNO	CANALES									
		1	2	3	4	5	6	7	8	9	10
4.30	4.40	-	SH								
4.55	4.65	-									
4.80	4.90	-				SD					
5.10	5.20	-	SDS								
5.40	5.50	-									
5.80	5.90	-									
6.20	6.30	-									
6.60	6.70	-									
7.00	7.10	-									
7.40	7.50	-			SF				SF		
7.90	8.00	-									E
8.40	8.50	-							E		
8.90	9.00	-	SK								
9.15	9.25	-									
9.65	9.75	-									
10.20	10.30	-									F
10.80	10.90	-									
11.20	11.30	-					E				
11.70	11.80	-							F		
12.40	12.50	-									
13.10	13.20	-									
13.90	14.00	-									
14.90	15.00	-	SF								J
15.90	16.00	-									
18.60	18.70	-									
21.10	21.20	-							J		
23.50	23.60	-				F					
27.90	28.00	-									
31.40	31.50	-									M°
37.40	37.50	-					J		M°		
49.90	50.00	-						M°			